

Coolgear, Inc. 5120 110th Ave N Clearwater, FL 33760 USA **P:** +1-727-209-1300 **F:** +1-727-209-1302 **coolgear.com** 

### Technical Data Sheet Rev 06-240920

# 10 Port USB 3.2 Gen 1 Hub Surge Protection w/ Din Rail Mounting

Model Number: CG-10U3AML



Black

#### **Features**

- Compliant with USB Specifications 3.2 Gen 1
- Provides 10 USB3.2 Gen 1 Downstream Facing Ports
- Supports 5Gbps, 480Mbps, 12Mbps and 1.5Mbps Speed
- Supports +7~24V DC Wide Range Self-power Input
- Supports 15KV ESD Protection for Each Port

## **Package Contents**

- 2-Pin Terminal Block
- DIN rail bracket
- Screw Lock USB Cable
- Screw Pack

OVERVIEW		
Model No	CG-10U3AML	
Product Type	USB Hub	
Compliance	None or N/A	
UPC	045079163126	
Country of Origin	Taiwan	
LED indicators	None or N/A	
Chipset	GL3523	
Electrical Protections	N/A	
PHYSICAL		
Ship Weight (lbs)	1.21 lbs	
Ship Weight (kg)	0.55 kg	
Item Weight	0.731 lbs	
Length	7.78 inches	
Width	1.22 inches	
Height	2.18 inches	
Material	Steel	

Din-Rail | Surface Mount | Wall Mount

Color

Mountable



Specifications Cont.	
CONNECTIONS	
USB Specification	USB 3.2 Gen 1
Upstream Port Type	Туре В 3.0
Maximum Data Rate	5 Gbps
Downstream Port Count	10
Downstream Port Type	10x Type A USB 3.2 G1 / 3.0
Works as Standalone Charger	Y - Can be used without Host
Can be Bus Powered	Y - Supports Bus Power
Bus Power Isolation	Υ
POWER	
Input Voltage	12 ~ 24V DC
Max Power Draw	75W
Max Per Port Draw	1.5A(7.5W)
ENVIRONMENTAL	
Operating Temperature	0C ~ 70C
Storage Temperature	-20C ~ 75C
Operating Humidity	5% to 95% RH
OS SUPPORT	
Supported Operating Systems	Linux   Windows 10   Windows 8   Windows 7   Windows Vista   Windows XP
WARRANTY	
Warranty Period	1 Year
PRODUCT URL	
Product Page	https://www.coolgear.com/product/10-port-usb-3-0-hub-integrated-surge-protection-w-din-rail- mounting-kit

**USB CHARGING & CONNECTIVITY EXPERTS** 



# **We Speak Your Speak**

When you reach out to Coolgear support, you'll find yourself in the hands of a solution-oriented and knowledgeable expert ready to answer whatever question you throw at them. Go ahead, test us.

Visit Support