

Technical Data Sheet Rev 06-250801

1-Port USB to Serial Adapter (RS-232/422/485) , DIN-rail

Model Number: USB-COMi-PRO



Features

- Adds one RS-232, RS-422, or RS-485 serial port via USB connection.
- Software configuration for easy RS-232, RS-422, RS-485 mode settings.
- Remote Serial Port Sharing: allows remote access to USB serial port regardless of its physical location.
- 512 byte transmit buffer and 512 byte receive buffer using buffer smoothing technology for high data throughput.
- Monitor LEDs of Power, TxD, RxD indicating power & port status.

Package Contents

- Driver/Software Disk
- USB Cable
- USB Serial Adapter

Specifications

OVERVIEW

Model No	USB-COMi-PRO	Product Type	USB Serial Adapter
Compliance	None or N/A	UPC	045079162907
Country of Origin	Taiwan	LED indicators	Port Status Power TX/RX
Chipset	FTDI	Electrical Protections	15KV

PHYSICAL

Ship Weight (lbs)	0.54 lbs	Ship Weight (kg)	0.24 kg
Item Weight	0.29375 lbs	Length	2.24409 inches
Width	2.99213 inches	Height	0.905512 inches
Material	Steel	Color	Black
Mountable	Surface Mount	Cable Length (in)	36
Cable Length (m)	0.91		

Specifications Cont.

CONNECTIONS

Connector(s)	5-pin Terminal Block DB9 Male w/ Nuts
Maximum Data Rate	RS-232: up to 1Mbps RS-422/485: up to 3Mbps

SERIAL SPECS

Maximum Data Rate	3 Mbaud
Minimum Data Rate	300 baud/bps
Data Bits	7, 8
Parity	None, Even, Odd, Mark, Space
Stop Bits	1, 2
Flow Control	Hardware (RTS, CTS), XON/XOFF
FIFO	512 bytes transmit and receive
Serial Modes	RS232 RS422 RS485
RS232 Signals	DCD, RxD, TxD, DTR, GND, DSR, RTS, CTS, RI
RS422 Signals	TxD-, TxD+, RxD+, RxD-, GND, RTS-, RTS+, CTS+, CTS-
RS485 2-wire Signals	DATA-, DATA+, GND
RS485 4-wire Signals	TxD-, TxD+, RxD+, RxD-, GND

ENVIRONMENTAL

Operating Temperature	0C ~ 55C
Storage Temperature	-20C ~ 75C
Operating Humidity	5% to 95% RH

OS SUPPORT

Supported Operating Systems	Linux OSX 10 Windows 11 Windows 10 Windows 8 Windows 7 Windows Vista Windows XP
-----------------------------	---

WARRANTY

Warranty Period	1 Year
-----------------	--------

PRODUCT URL

Product Page	https://www.coolgear.com/product/1-port-usb-to-serial-adapter-rs-232-422-485-din-rail
--------------	---

USB CHARGING & CONNECTIVITY EXPERTS



We Speak Your Speak

When you reach out to Coolgear support, you'll find yourself in the hands of a solution-oriented and knowledgeable expert ready to answer whatever question you throw at them. Go ahead, test us.

[Visit Support](#)